

Freedom Antenna® Cell Phone Signal Booster



- ◆ The Freedom Antenna® reduces dropped calls and improves signal reception in areas of limited cell network coverage
- ◆ Sleek, low profile design is excellent for use anywhere you are, traveling, in the office, at home, or in your vehicle
- ◆ Innovative, patented circuit with as much as 3dBi gain in a small, portable and attractive design
- ◆ Omni-directional antenna design that provides 360 degrees of coverage
- ◆ Ultra-wide frequency range coverage works with all cellular frequencies including UMTS, 3G, GSM, PCS, and even Wi-Fi® 802.11b/g
- ◆ An integral desktop stand is also included

Mechanical Specifications	
Length	5.8in (cm)
Width	3.3in (cm)
Depth	0.75in (cm)
Color	Charcoal Gray
Connection	Integral 3ft low loss cable with FME Jack connector

Electrical Specifications	
Frequency Range	800 MHz to 2.5 GHz
Gain	3dBi typ.
Coverage	Omni-directional 360deg
VSWR	≤2:1 typ.
Power Rating	50 watts
Impedance	50 ohms

Shipping Information	
Sizes and Weights	Description
8in x 5in x 10in (20.3cm x 12.7cm x 25.4cm) 3lb, (1.36kg)	Bulk pack includes 6 antennas in an over pack box

Ordering Information	
Part #	Description
ARC-FR0803R30	ARC Freedom Antenna®, FME Jack Standalone

www.freedomantenna.com

Specifications subject to change without notice

See www.freedomantenna.com for warranty information